



■ Features :

- Protections: Short circuit / Overload / Over voltage
- Cooling by free air convection
- LED indicator for power on
- 100% full load burn-in test
- All using 105°C long life electrolytic capacitors
- * Withstand 300VAC surge input for 5 second
- * High operating temperature up to $70^\circ\!\text{C}$
- Withstand 5G vibration test
- High efficiency, long life and high reliability
- 3 years warranty

SPECIFICATION



MODEL		RQ-125B				RQ-125C				RQ-125D				
	OUTPUT NUMBER	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH4	CH1	CH2	СНЗ	CH4	
OUTPUT	DC VOLTAGE	5V	12V	-5V	-12V	5V	15V	-5V	-15V	5V	12V	24V	-12V	
	RATED CURRENT	11A	4.5A	1A	0.5A	10A	4A	1A	0.5A	8A	2.5A	2A	0.5A	
		2 ~ 12A	0.5 ~ 4.5A	0.1 ~ 1A	0 ~ 1A	2 ~ 12A	0.5 ~ 4A	0.1 ~ 1A	0 ~ 1A	2 ~ 12A	0.5 ~ 4A	0.1 ~ 2.5A	0 ~ 1A	
	RATED POWER Note.6	120W				122.5W				124W				
	RIPPLE & NOISE (max.) Note.2	80mVp-p 120mVp-p 80mVp-p 80mVp-p								80mVp-p 120mVp-p 150mVp-p 80mVp-p				
	VOLTAGE ADJ. RANGE	CH1: 4.75 ~ 5.5V				CH1: 4.75 ~ 5.5V				CH1: 4.75 ~ 5.5V				
	VOLTAGE TOLERANCE Note.3		+8,-3%	+6,-10%	±5.0%	±2.0%	+8,-3%	+6,-10%	±5.0%	±2.0%	+8,-3%	±8.0%	±5.0%	
	LINE REGULATION Note.4	±0.5%	±1.0%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	±1.0%	
	LOAD REGULATION Note.5	±1.0%	±3.0%	±6.0%	±2.0%	±1.0%	±3.0%	±6.0%	±2.0%	±1.0%	±3.0%	±5.0%	±2.0%	
	SETUP, RISE TIME	500ms, 20	ms/230VA	C 120	00ms, 30m	s/115VAC a	it full load			1	1			
	HOLD UP TIME (Typ.)	25ms/230VAC 30ms/115VAC at full load												
INPUT	VOLTAGE RANGE	88 ~ 132VAC / 176 ~ 264VAC selected by switch 248 ~ 373VDC(Withstand 300VAC surge for 5sec. Without damage)												
	FREQUENCY RANGE	47 ~ 63Hz									<u> </u>			
	EFFICIENCY (Typ.)	79%				80%				82%				
	AC CURRENT (Typ.)	3A/115VA	3A/115VAC 2A/230VAC											
	INRUSH CURRENT (Typ.)	COLD START 40A/230VAC												
	LEAKAGE CURRENT	<2mA / 24	<2mA / 240VAC											
PROTECTION		110 ~ 150% rated output power												
	OVERLOAD	Protection type: Hiccup mode, recovers automatically after fault condition is removed												
		CH1: 5.75 ~ 6.75V												
	OVER VOLTAGE	Protection type : Hiccup mode, recovers automatically after fault condition is removed												
ENVIRONMENT	WORKING TEMP.	-25 ~ +70°C (Refer to "Derating Curve")												
	WORKING HUMIDITY	20 ~ 90%	RH non-co	ndensing										
	STORAGE TEMP., HUMIDITY	-40 ~ +85	-40 ~ +85°C, 10 ~ 95% RH											
	TEMP. COEFFICIENT	$\pm 0.03\%$ °C (0 ~ 50°C)on +5V output												
	VIBRATION	10 ~ 500Hz, 5G 10min./1cycle, period for 60min. each along X, Y, Z axes												
	SAFETY STANDARDS	UL60950-1, TUV EN60950-1 approved												
SAFETY &	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC												
EMC	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH												
(Note 7)	EMC EMISSION	Compliance to EN55022 (CISPR22) Class B, EN61000-3-2,-3												
	EMC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, EN61000-6-2 (EN50082-2), heavy industry level, criteria A												
OTHERS	MTBF	203.1Khrs min. MIL-HDBK-217F (25°C)												
	DIMENSION	199*98*38mm (L*W*H)												
	PACKING	0.7Kg; 20pcs/14Kg/0.8CUFT												
NOTE	Ripple & noise are measured Tolerance: includes set up Line regulation is measured Load regulation is measured Each output can work within The power supply is consid EMC directives. For guidan (as available on http://www.	specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature. neasured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor. set up tolerance, line regulation and load regulation. seasured from low line to high line at rated load. seasured from 20% to 100% rated load, and other output at 60% rated load. fk within current range. But total output power can't exceed rated output power. considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." ://www.meanwell.com) s is measured at cold first start. Turning ON/OFF the power supply very quickly may lead to increase of the set up time.												



