



■ Features :

- Universal AC input / Full range
- Protections: Short circuit / Overload / Over voltage
- Cooling by free air convection
- LED indicator for power on
- 100% full load burn-in test
- All using 105°C long life electrolytic capacitors
- * Withstand 300VAC surge input for 5 second
- * High operating temperature up to 70°C
- Withstand 5G vibration test
- · High efficiency, long life and high reliability
- 3 years warranty





CBCE

SPECIFICATION

SPECIFIC	DT 05A						DT CED							
MODEL		RT-65A		RT-65B			RT-65C			RT-65D				
ОИТРИТ	OUTPUT NUMBER	CH1	CH2	CH3	CH1	CH2	CH3	CH1	CH2	CH3	CH1	CH2	CH3	
	DC VOLTAGE	5V	12V	-5V	5V	12V	-12V	5V	15V	-15V	5V	24V	12V	
	RATED CURRENT	6A	2.8A	0.5A	5A	2.8A	0.5A	5A	2.2A	0.5A	4A	1.5A	1A	
	CURRENT RANGE Note.6	0.5 ~ 8A	0.2 ~ 3.5A	0 ~ 1A	0.5 ~ 8A	0.2 ~ 3.5A	0 ~ 1A	0.5 ~ 8A	0.2 ~ 3A	0 ~ 1A	0.5 ~ 8A	0.2 ~ 2A	0.1 ~ 1A	
	RATED POWER Note.6	66.1W		64.6W		65.5W		68W						
	RIPPLE & NOISE (max.) Note.2			80mVp-p 120mVp-p 80mVp-p		80mVp-p 120mVp-p 80mVp-p		80mVp-p 150mVp-p 120mVp-p						
	VOLTAGE ADJ. RANGE	CH1: 4.75 ~ 5.5V		CH1: 4.75 ~ 5.5V			CH1: 4.75 ~ 5.5V			CH1: 4.75 ~ 5.5V				
	VOLTAGE TOLERANCE Note.3	±2.0%	±6.0%	±5.0%	±2.0%	±6.0%	±5.0%	±2.0%	+8,-4%	±5.0%	±2.0%	+4,-6%	±6.0%	
	LINE REGULATION Note.4	$\pm 0.5\%$	±1.5%	$\pm 0.5\%$	$\pm 0.5\%$	±1.5%	±0.5%	±0.5%	±1.5%	±0.5%	±0.5%	±1.5%	±2.0%	
	LOAD REGULATION Note.5	$\pm 1.0\%$	\pm 3.0%	±1.0%	$\pm 1.0\%$	±3.0%	±1.0%	±1.0%	$\pm 3.0\%$	±1.0%	±1.0%	±3.0%	±4.0%	
	SETUP, RISE TIME	500ms, 20ms/230VAC 1200ms, 30ms/115VAC at full load												
	HOLD UP TIME (Typ.)	60ms/230VAC 14ms/115VAC at full load												
INPUT	VOLTAGE RANGE	88 ~ 264VAC 125 ~ 373VDC (Withstand 300VAC surge for 5sec. Without damage)												
	FREQUENCY RANGE	47 ~ 63Hz												
	EFFICIENCY(Typ.)	77%			77%			78%			79%			
	AC CURRENT (Typ.)	2A/115VAC 1.2A/230VAC												
	INRUSH CURRENT (Typ.)	COLD START 40A/230VAC												
	LEAKAGE CURRENT	<2mA / 240VAC												
PROTECTION	OVERLOAD	110 ~ 150% rated output power												
		Protection type: Hiccup mode, recovers automatically after fault condition is removed												
	OVED VOLTACE	CH1: 5.75 ~ 6.75V												
	OVER VOLTAGE	Protection type: Hiccup mode, recovers automatically after fault condition is removed												
ENVIRONMENT	WORKING TEMP.	-25 ~ +70°	-25 ~ +70°C (Refer to "Derating Curve")											
	WORKING HUMIDITY	20 ~ 90% RH non-condensing												
	STORAGE TEMP., HUMIDITY	-40 ~ +85°C, 10 ~ 95% RH												
	TEMP. COEFFICIENT	$\pm 0.03\%$ $^{\circ}$ C (0 ~ 50 $^{\circ}$ C)on +5V output												
	VIBRATION	10 ~ 500Hz, 5G 10min./1cycle, period for 60min. each along X, Y, Z axes												
	SAFETY STANDARDS	UL60950-1, TUV EN60950-1 approved												
SAFETY &	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC												
EMC	ISOLATION RESISTANCE	TANCE I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C/ 70% RH												
(Note 7)	EMC EMISSION	Compliance to EN55022 (CISPR22) Class B, EN61000-3-2,-3												
	EMC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, EN61000-6-2 (EN50082-2), heavy industry level, criteria A												
OTHERS	MTBF	254.6Khrs min. MIL-HDBK-217F (25°C)												
	DIMENSION	129*98*38	3mm (L*W*	H)										
	PACKING	0.44Kg; 30	Opcs/13.2K	g/0.72CUF	Т									
NOTE	 All parameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature. Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor. Tolerance: includes set up tolerance, line regulation and load regulation. Line regulation is measured from low line to high line at rated load. Load regulation is measured from 20% to 100% rated load, and other output at 60% rated load. Each output can work within current range. But total output power can't exceed rated output power. 													

- Each output can work within current range. But total output power can't exceed rated output power.
 The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies."
 (as available on http://www.meanwell.com)



